

## Main Breaker Mounting Kits with Breakers for P1 Panels

(250A and lower can be used as subfeed kits also)

Original P1 Catalog No. (QJ/QR type listed where applicable)	Revised P1 Catalog No. (QJ/QR type listed where applicable)	Description	Ratings		
			QJ 240V	QR 240V	480V
MBKED3100	MBKED3100A	Kit w/3-pole ED4 100A breaker	65KA		18KA
MBKED3125	MBKED3125A	Kit w/3-pole ED4 125A breaker	65KA		18KA
MBKQJ1125 / MBKQR1125	MBKQJ1125A / MBKQR1125A	Kit w/2-pole QJ2/QR2 125A breaker	10KA	10KA	—
MBKQJ1150 / MBKQR1150	MBKQJ1150A / MBKQR1150A	Kit w/2-pole QJ2/QR2 150A breaker	10KA	10KA	—
MBKQJ1175 / MBKQR1175	MBKQJ1175A / MBKQR1175A	Kit w/2-pole QJ2/QR2 175A breaker	10KA	10KA	—
MBKQJ1200 / MBKQR1200	MBKQJ1200A / MBKQR1200A	Kit w/2-pole QJ2/QR2 200A breaker	10KA	10KA	—
MBKQJ1225 / MBKQR1225	MBKQJ1225A / MBKQR1225A	Kit w/2-pole QJ2/QR2 225A breaker	10KA	10KA	—
MBKQJ3125 / MBKQR3125	MBKQJ3125A / MBKQR3125A	Kit w/3-pole QJ2/QR2 125A breaker	10KA	10KA	—
MBKQJ3150 / MBKQR3150	MBKQJ3150A / MBKQR3150A	Kit w/3-pole QJ2/QR2 150A breaker	10KA	10KA	—
MBKQJ3175 / MBKQR3175	MBKQJ3175A / MBKQR3175A	Kit w/3-pole QJ2/QR2 175A breaker	10KA	10KA	—
MBKQJ3200 / MBKQR3200	MBKQJ3200A / MBKQR3200A	Kit w/3-pole QJ2/QR2 200A breaker	10KA	10KA	—
MBKQJ3225 / MBKQR3225	MBKQJ3225A / MBKQR3225A	Kit w/3-pole QJ2/QR2 225A breaker	10KA	10KA	—
MBKQJ1125H / MBKQR1125H	MBKQJ1125HA / MBKQR1125HA	Kit w/2-pole QJ2H/QR2 125A breaker	42KA	65KA	—
MBKQJ1150H / MBKQR1150H	MBKQJ1150HA / MBKQR1150HA	Kit w/2-pole QJ2H/QR2 150A breaker	42KA	65KA	—
MBKQJ1175H / MBKQR1175H	MBKQJ1175HA / MBKQR1175HA	Kit w/2-pole QJ2H/QR2 175A breaker	42KA	65KA	—
MBKQJ1200H / MBKQR1200H	MBKQJ1200HA / MBKQR1200HA	Kit w/2-pole QJ2H/QR2 200A breaker	42KA	65KA	—
MBKQJ1225H / MBKQR1225H	MBKQJ1225HA / MBKQR1225HA	Kit w/2-pole QJ2H/QR2 225A breaker	42KA	65KA	—
MBKQJ3125H / MBKQR3125H	MBKQJ3125HA / MBKQR3125HA	Kit w/3-pole QJ2H/QR2 125A breaker	42KA	65KA	—
MBKQJ3150H / MBKQR3150H	MBKQJ3150HA / MBKQR3150HA	Kit w/3-pole QJ2H/QR2 150A breaker	42KA	65KA	—
MBKQJ3175H / MBKQR3175H	MBKQJ3175HA / MBKQR3175HA	Kit w/3-pole QJ2H/QR2 175A breaker	42KA	65KA	—
MBKQJ3200H / MBKQR3200H	MBKQJ3200HA / MBKQR3200HA	Kit w/3-pole QJ2H/QR2 200A breaker	42KA	65KA	—
MBKQJ3225H / MBKQR3225H	MBKQJ3225HA / MBKQR3225HA	Kit w/3-pole QJ2H/QR2 225A breaker	42KA	65KA	—
MBKFD3150	MBKFD3150A	Kit w/3-pole FXD6 150A breaker	65KA		35KA
MBKFD3175	MBKFD3175A	Kit w/3-pole FXD6 175A breaker	65KA		35KA
MBKFD3200	MBKFD3200A	Kit w/3-pole FXD6 200A breaker	65KA		35KA
MBKFD3225	MBKFD3225A	Kit w/3-pole FXD6 225A breaker	65KA		35KA
MBKFD3250	MBKFD3250A	Kit w/3-pole FXD6 250A breaker	65KA		35KA
MBKJD1300 <sup>Ⓢ</sup>	MBKJD1300A <sup>Ⓢ</sup>	Kit w/2-pole JXD6 300A breaker	65KA		35KA
MBKJD3300 <sup>Ⓢ</sup>	MBKJD3300A <sup>Ⓢ</sup>	Kit w/3-pole JXD6 300A breaker	65KA		35KA
MBKJD1400 <sup>Ⓢ</sup>	MBKJD1400A <sup>Ⓢ</sup>	Kit w/2-pole JXD6 400A breaker	65KA		35KA
MBKJD3400 <sup>Ⓢ</sup>	MBKJD3400A <sup>Ⓢ</sup>	Kit w/3-pole JXD6 400A breaker	65KA		35KA
MBKJD12300 <sup>Ⓢ</sup>	MBKJD12300A <sup>Ⓢ</sup>	Kit w/2-pole JXD2 300A breaker	65KA		—
MBKJD32300 <sup>Ⓢ</sup>	MBKJD32300A <sup>Ⓢ</sup>	Kit w/3-pole JXD2 300A breaker	65KA		—
MBKJD12400 <sup>Ⓢ</sup>	MBKJD12400A <sup>Ⓢ</sup>	Kit w/2-pole JXD2 400A breaker	65KA		—
MBKJD32400 <sup>Ⓢ</sup>	MBKJD32400A <sup>Ⓢ</sup>	Kit w/3-pole JXD2 400A breaker	65KA		—

Ⓢ Kits are for Main only. New "Revised P1" kits can be used for either top feed or bottom feed.

NOTE: "Revised P1" Kits above only work for interior numbers ending in "T" or "N". Use "Original P1" kits for all others.

## Branch Breakers Selection for P1

### Selection Guide

1. Select breaker type.
2. Select required amperage.
3. Select number of poles.
4. Select branch breaker catalog numbers.
5. Select ground bar and filler plates.  
(See replacement parts & accessories on Page 11-11.)



**300A Main installed.**  
These Revised P1 kits can now be used as top or bottom feed.

## AFCI – Combination Type Arc Fault Circuit Interrupter

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BAF2 1-pole	15	BA115AFC	10	—	—
	20	BA120AFC	10	—	—
BAFH2 1-pole	15	BA115AFCH	22	—	—
	20	BA120AFCH	22	—	—
HBAF2 1-pole	15	BA115AFCHH	65	—	—
	20	BA120AFCHH	65	—	—
BAF 2-pole	15	B215AFC	—	10	—
	20	B220AFC	—	10	—
BAFH 2-pole	15	B215AFCH	—	22	—
	20	B220AFCH	—	22	—

## Switching Neutrals

Breaker Type	Ampere Rating	Catalog Number	Maximum Interrupting Rating (kA)		
			120V AC	120/240V AC	240V AC
BG 2-Wire Common Trip	15	BG215■	10	—	—
	20	BG220■	10	—	—
	30	BG230■	10	—	—
BG 3-Wire Common Trip	15	BG315■	—	10	—
	20	BG320■	—	10	—
	30	BG330■	—	10	—

■ Built to order.

## AFCI – Branch Feeder Type Arc Fault Circuit Interrupter

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BAF2 1-pole	15	BA115AF	10	—	—
	20	BA120AF	10	—	—
BAF2H 1-pole	15	BA115AFH	22	—	—
	20	BA120AFH	22	—	—
HBAF2 1-pole	15	BA115AFHH	65	—	—
	20	BA120AFHH	65	—	—

## Dual Function AFCI/GFCI Circuit Breaker

Breaker Type	Ampere Rating	Catalog Number	Interrupting Ratings (kA) RMS Symmetrical Amperes		
			Volts AC		
			120	120/240	240
BFGA2 1-pole	15	B115DF	10	—	—
	20	B120DF	10	—	—
BFGAH2 1-pole	15	B115DFH	22	—	—
	20	B120DFH	22	—	—
HBFGA2 1-pole	15	B115DFHH	65	—	—
	20	B120DFHH	65	—	—